

Fluke 8840A Digital Multimeter

Digital Multimeter, 5.5 Digit

- 5.5 digit resolution
- True RMS ac volts and current(option 09)
- **DC Volts**
- 200 mV to 1000 V ranges
- **AC True RMS Volts (option 09)**
- 200 mV to 700 V ranges
- 20 Hz to 100 kHz bandwidth
- **Ohms**
- 200 ohms to 20 megohm ranges
- 2- or 4-wire selectable
- **DC Current**
- 2000 mA range
- **AC True RMS Current (option 09)**
- 2000 mA range
- 20 Hz to 5 kHz bandwidth
- HP-IB interface (option 05)
- 100, 120/220, 240 Vac $\pm 10\%$; 50, 60, 400 Hz operation
- Weight: 8 lb; Size: 89 mm (3.5 in)H x 216 mm (8.5 in)W x 371 mm (14.6 in)D



- Highly Legible Vacuum Fluorescent Display
- Intuitively Easy Front Panel Operation
- Basic DC Accuracy of 0.005% for 1 Year
- Up to 100 Readings Per Second
- Closed-Case Calibration (No Internal Adjustments)
- Built-In Self-Tests